

## High Power Battery Charge Controller

### Features

- 300W Total Power
- Regulated 12VDC or 24VDC Output Voltage
- Seamless Switchover From AC to Battery Power when AC Power Fails.
- Load Control to Prevent Battery Overdischarge. Automatic Recovery.
- Smart Charge program for GEL/AGM or WET type batteries
- Wide temperature operation



### Applications

- Wireless Base Stations, Cellular Base Stations
- Surveillance Systems
- Battery Backup Systems

### Description

The **TP-BC** series of smart battery chargers provide up to 300W of total power. Part of the power is allocated to the regulated load output and remaining power is allocated to battery charging. The smart battery charger is compatible with GEL/AGM type sealed lead acid batteries and also WET type lead acid batteries (like car batteries).

The load output is regulated so that output voltage does not exceed 12.5VDC on the 12V model and 24.5VDC on the 24V model. Also the load output will turn off when the battery voltage is low to prevent over discharge of the batteries which can shorten the useable life of the batteries. Load output will turn back on automatically when batteries have sufficient charge. The TP-BC series provides seamless switchover from AC power to battery power so there is no interruption which could reset a user's electronics. The charger auto-recovers from a power failure so no user action is necessary.

The charger has various protections for short circuit, overvoltage protection, overcurrent and reverse battery. It operates over a wide temperature range making it suitable for industrial applications.

The battery charger will not work without a battery connected.

A solar panel and solar charge controller can be added to the system if supplemental power from solar is desired.

There are various LEDs on the front panel to see status-at-a-glance of the Load Output, Charging Condition and AC Power Condition.

#### LED Indicators

- LOAD** (Load Power is Turned On = Green)
- PWR** (AC Power On = Yellow)
- BATT** ( Battery is Connected = Green)
- CHD** ( Battery is Fully Charged = Green)
- CHG** ( Battery is Charging = Yellow)
- WET / GEL** – Switch is positioned to WET(Green) or GEL(Yellow)

## Specifications

	TP-BC12-300	TP-BC24-300
<b>Total Power Available (for Load and Battery charging)</b>	300W	300W
<b>Nominal Battery Voltage</b>	12VDC	24VDC
<b>Load Output Min Current</b>	1A	1A
<b>Load Output Max Current</b>	12A	8A
<b>Overdischarge Protection</b>	10.7V Load off / 12.6V Load on	21.5V Load off / 25.2V Load on
<b>Battery Charge Max Current</b>	12A	12A* * if load current is 8A then battery charge current is 4.5A. If load current 6A then battery charge current is 6.5A
<b>Battery Charger Voltage</b>	WET Equalize = 14.6V, Float = 13.2V GEL Equalize = 14.2V, Float = 13.5V	WET Equalize = 28.8V, Float = 26.4V GEL Equalize = 28.4V, Float = 27V
<b>Load Regulation</b>	5%	
<b>Line Regulation / Ripple</b>	1%	
<b>Noise</b>	2%	
<b>Efficiency</b>	75% Minimum	
<b>Load and Battery Connections</b>	Screw Wire Terminal, 10 AWG MAXIMUM	
<b>EMC Standards</b>	FCC Class A , NE55022 Class A	
<b>Safety Standards</b>	UL1950, CSA 22.2, TUV EN60950	
<b>AC Power Input</b>	Selector Switch 120VAC / 230VAC , 50/60Hz	
<b>AC Input Current</b>	3.5A @ 115VAC / 1.8A @ 230VAC	
<b>Operating Temperature</b>	-20 to +60C (-4 to +140°F)	
<b>Operating Humidity (RH)</b>	Up to 90% (non condensing)	
<b>Cooling</b>	Temperature Controlled Fan	
<b>Storage Temperature</b>	-25 to +85°C (-13 to +185°F)	
<b>Storage Humidity</b>	Up to 90% (non-condensing)	
<b>Dimensions (LxWxH)</b>	250 x 185 x 55mm (9.8 x 7.3 x 2.2")	
<b>Weight</b>	2.4kg (5.2lb)	

### Notes:

- All shipments F.O.B. Bluffdale, UT 84065
- TP-BC Series carry a 1 year warranty



## System Ordering:

**TP-BC12-300** 300W Smart Battery Charger with regulated 12VDC load output with US Power Cord\*

**TP-BC24-300** 300W Smart Battery Charger with regulated 24VDC load output with US Power Cord\*

\*Add an "E" suffix for Euro power cord

## For further information contact:

[Tyconpower.com](http://Tyconpower.com)



693 Draper Heights Way Ste 102  
Draper, UT 84020  
PH: 801-432-0003  
FAX: 801-618-4220